

FIRE ALARM ACCESSORIES

WSL 035 STROBE LIGHT

- Dimensions: 185x130x70mm
- Max Alarm Volume: ~100dB
- Working surrounding humidity: ~95%
- Operating temper : -10~+55°C
- Working voltage: 22-30DC for use with fire alarm system
Current: 70mA
- Flash intensity:~1.2WS
- Flash cycle:<2.0sec
- Frequency life of flash lamp: ~30,000 times
- 3 kinds of Alarm sound: Ambulance, Fire Engine, Police vehicle
- Different colors are available




WMCP 026 MANUAL CALL POINT

- Dimensions: 90x90x45mm
- Operating temper.: -20°C +50°C
- Voltage: DC18-32V
- Alarm current:5mA<1<10mA
- Color: Red



WUV 001 SERVICE ALERT

- To alert users to call their service company
- To alert users to call AC maintenance
- Service for UV bulbs service
- To alert elderly people to take medicine
- To alert staff in the hospital to take care of patience when time comes, etc .



WRM 100 Relay Module for WSD 827-I

The relay module for WSD 827-I models (with Interconnection function only)

This module makes the Stand-Alone Photoelectric Smoke Detector WSD 827-I (with interconnect) capable of communicating to the fire station, alert users, dial a pre-programmed number etc.

WELS Secutrons (P) Ltd

'Mahalakshmi Buildings', 92, Mount Road, Guindy, Chennai 600032 INDIA.
Tel: 91-44-2355831/ 2351574 / 2350816 Fax: 91-44-2352030 <http://www.wels.co.in>

FIRE ALARM ACCESSORIES

WLD-FS97P - Mini Siren with Strobe

- This model intends to could substitute traditional mechanical fire alarm bells
- Waterproof & easy to install design
- Operating voltage and current:
 - 12V-28VDC, (typical voltage: DC 24V)
 - Siren: 40mA, strobe: 250mA (at DC 24V)
- Siren tone: sweep
- Siren output: 105 +/- 3dB(at 1 meter)
- Size(mm): 82(L) x 82(W) x 34(H)
- Power cord: 1 ft. (AWG 24) in general



WLD-582 Alarm with Strobe and Battery Backup Bell Box

- Built-in anti-tamper switch/with feed-back terminal
- Weatherproof, UV-proof, hi-impact (3mm thick polycarbonate housing)
- Auto-recharging battery circuit
- Powerful siren output: 115 +/-3dB (at 1 foot)
- Operating voltage current:
 - 10V to 14V DC, (typical voltage: DC 12V)
 - Siren: 150mA, strobe: 250mA (at DC 12V)
- Battery capacity: 280MAH
- Size (mm): 241 x 160 x 51 (L x W x H)
- Optional power cord: four-thread telephone cord, 10 meters long



WLD-69 Internal/External Siren with Strobe

- The visible curve of the strobe cover is designed using anthropometrics
- Rain proof, UV proof, suitable for indoor or outdoor use
- High impact (polycarbonate housing)
- Operating voltage and current:
 - DC 12V type: 10V-24V DC, (typical voltage) (at DC 12V) siren: 120mA, strobe: 130mA
 - DC 24V type: 20V-28V DC, (at DC 24V) siren: 120mA, strobe: 130mA
- Siren tones: siren (typical tone), sweep, hi-low
- Siren output: 110 +/- 3dB (at 1 ft.)
- Size(mm): 122(L) x 73(W) x 43(H)
- Power cord: 1 ft. (AWG 24) in general



FIRE ALARM ACCESSORIES

WLD-29 Sirens with Strobe

- Its camouflage appearance disguises its actual functions, protecting itself so it can perform its normal functions
- Rainproof, UV proof, High impact (polycarbonate housing)
- Operating voltage and current:
 - 10VDC to 14VDC, (typical voltage: 12VDC)
 - Siren: 250mA, strobe: 250mA (at 12VDC)
- Siren tone: siren (typical tone)
- Siren output: 110 +/- 3dB (at 1 foot)
- Size (L x W x H): 122 x 72 x 35mm
- Power cord: 1 foot (24 AWG) in general

